

PYRAMID

AC RECEIVER

PY-AC...

PY-ACW-L RS485, Low speed, boxed
PY-ACB-L RS485, Low speed, PCB
PY-ACW-2-H RS485, High speed, boxed

PY-ACB-2-H RS485, High speed, PCB
PY-ACW-H FTT10, High speed, boxed
PY-ACB-H FTT10, High speed, PCB



FEATURES

- Fixed speed outputs for 240V AC pan and Tilt units
- Switched on/off functions for Pan, Tilt, zoom, focus
- Manual and auto iris control from the receiver
- 4 auxiliary switched functions
- Up to 128 preset positions per camera
- Video gain and lift to compensate for long cable runs
- Random Patrol
- Electronic end stops
- Privacy zones
- Installation diagnostic leds and test button

Specifications

Video Input	1 V pk-pk PAL/NTSC
Video Lift and Gain	Gain >5dB remotely programmable from the keyboard Lift >4dB at 4MHz remotely programmable from the keyboard
Drives	Pan/Tilt relay driven Lens Zoom, focus and iris. 100mA 6-12V with initial inching function Auto iris Programmable with manual override, reverting to programmable after time delay
Relays	4 Aux Programmable latching or timed Outputs 2A max. @ 240V Fuse 10A anti-surge Anti-tamper Built-in or external
Presets	Quantity 128 on pan, tilt, zoom and focus Accuracy 10bit ±least significant bit
Network plug-in cards	PY-COM, PY-FTT, PY-FIM
Dimensions	PCB version 136 x 160 x 40mm Weather proof box version 280 x 280 x 130mm
Power supply	24V DC
Power consumption	8.5W nominal
Weight	5kg
Connections	Removable screw-terminal blocks



BAXALL LIMITED