



# GSM Gateway



- ▶ High sensitivity of receiving and sending,
- ▶ Strong emitting power
- ▶ Emulates switching equipment
- ▶ Phone/SIM card locking function
- ▶ Supports Office PBX
- ▶ Backup power system

The GSM Gateway of Bosch is designed to connect a Carephone to a monitoring center through the GSM network. This type of connection is independent of the fixed-line network or broadband connection of the subscriber. The GSM Gateway is meant to be used as a backup system.

## System Overview

The GSM Gateway contains a modem which translates the dial request into a GSM protocol. The GSM Gateway thus functions similarly to a GSM telephone with an analog connection.

The GSM Gateway is equipped with a series of LEDs that show its status and signal strength. A SIM card slot allows easy programming.

Additional functions are available such as quick dialing, forbidden calls indication and volume adjustment.

## Installation/Configuration Notes

It is recommended to avoid using prepaid cards within the GSM Gateway.

Use only rechargeable batteries as backup power system.

## Parts Included

Quant.	Component
1	GSM Gateway
1	Power adapter
1	Set of backup batteries
1	Antenna with cable
1	RJ11 cable
1	User manual

## Technical Specifications

Switched-mode power supply	110-240V, DC7.5V, 1.5A 110-240V, DC12V, 1.0A
Backup Batteries	NiMH AA 1100mAh 1.2V (5 pieces)
Battery life	In standby: approx. 7 hours In continuous talk: approx. 1 hour
Operating temperature	0°C to +55°C
Relative humidity	10 to 95%
Working frequency (MHz)	Up: 890~915 1710~1785 1850~1910 Down: 935~960 1805~1850 1930~1990
Transmission	< 2 W
Reception	- 103 dBm
Gain	2 dBm

Noise	< 60 dBA
Stability	> 2.5 ppm
Distance between phone and GSM Gateway	maximum 100 m

### Ordering Information

#### GSM Gateway

External modem for Carephones 52+ and 62.

#### CRS-GSM-HTS

**Americas:**  
Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**  
Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6258 5511  
Fax: +65 6571 2698  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

#### Represented by