



DS1108i Glassbreak Detector



The DS1108i Detector uses microprocessor-based sound analysis technology (SAT) to listen for the specific frequencies associated with breaking glass. The DS1108i can be used to detect breakage of plate, tempered, laminated and wired glass types. A built-in environmental test feature alerts the installer to false alarm hazards in harsh environments. The round enclosure mounts on ceilings or walls.

Functions

Signal Processing

Audio signals are analyzed using microprocessor-based SAT and must produce specific frequency, signature, and timing relationships to cause an alarm. The sophistication of this processing technique ensures proper catch performance while eliminating false alarms.

Test Features

The magnet-operated test mode provides a location verification and operational test when using the optional DS1110i Glassbreak Tester. The test mode also includes an environmental test that alerts the installer to possible false alarm sources caused by ambient noise. The automatic sound check feature allows the end user to verify that the detector is powered and functioning by clapping hands. An externally-visible alarm LED indicates an alarm or test condition and can be programmed to latch if desired.

- ▶ Microprocessor-based sound analysis technology (SAT)
- ▶ Automatic environmental test circuitry
- ▶ Sound check

Certifications and Approvals

Region	Certification	
Europe	CE	89/336/EEC, EN55022:1998 +A1:2000 +A2:2003, EN50130-4:1996 +A1:1998 +A2:2003, EN61000-4-2:1995 +A1:1998 +A2:2001, EN61000-4-3:2002 +A1:2003, EN61000-4-4:1995 +A1:2000 +A2:2001, EN61000-4-5:1995 +A1:2001, EN61000-4-6:1996 +A1:2001 +A2:2001, EN61000-4-11:1994 +A1:2001, EN60950-1:2001 +A11:2004
USA	UL	DS1108i: ANSR: Intrusion Detection Units (UL639)

Installation/Configuration Notes

Note Glassbreak detectors are intended only as a component of a perimeter protection system. They should always be used in conjunction with motion sensors.

Mounting

Mount the DS1108i detector on the ceiling, or on the wall opposite or adjacent to the window. Coverage depends on room acoustics and window size.

Standard Coverage

7.6 m (25 ft) for glass sizes over 30.5 cm x 30.5 cm
(12 in. x 12 in.).

Parts Included

Quant.	Component
1	Detector
1	Literature – Installation Guide

Technical Specifications**Electrical**

Current: 21 mA nominal at 12 VDC

Voltage: 9 VDC to 15 VDC

Environmental

Operating Temperature: -29°C to +49°C (-20°F to +120°F)
*For UL Certified installations, 0°C to +49°C
(+32°F to +120°F)*

Radio Frequency Interference (RFI) Immunity: No alarm or setup on critical frequencies in the range from 26 MHz to 950 MHz at 50 V/m.

Mechanical

Dimensions (HxDiameter): 2.1 cm x 8.6 cm (0.83 in. x 3.4 in.)

Material: High-impact ABS plastic enclosure

Outputs

Alarm: Normally-closed (NC) reed relay rated at 3.5 W, 125 mA at 28 VDC for resistive loads

Tamper: Normally-closed (NC) cover-activated tamper switch with separate terminals. Contacts rated at 28 VDC, 125 mA maximum.

Ordering Information**DS1108i Glassbreak Detector DS1108i**

Round detector uses microprocessor-based sound analysis technology (SAT) to listen for the specific frequencies associated with breaking glass

Accessories**DS1110i Glassbreak Tester DS1110i**

Used to test DS1101i, DS1102i, DS1103i, and DS1108i Glass Break Detectors. Powered by a 9 V alkaline battery (supplied).

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: +31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6258 5511
Fax: +65 6571 2698
apr.securitysystems@bosch.com
www.boschsecurity.com