



DSX Access Systems, Inc.

FIPs 201 Enrollment Reader



- **USB Connected**
- **Programmed by DSX**
- **Formatted for WinDSX SQL**
- **Extracts CHUID for unique card holder identification**
- **Includes Issue Level**
- **Extracts Expiration Date**
- **Inserts 16 digit CHUID in Code field**
- **Inserts Expiration Date in Stop Date field.**
- **LED flashes and beeps when card is read**

FIPS 201 Enrollment Reader

Size

4.2"W x 2.5"H x .875"D

Weight

.45lbs

Power Requirements

USB

Warranty

Limited 1 Year

13.56 MHZ / FCC, RoHS

FIPS 201 Enrollment Reader

USB connected Reader. This reader is preprogrammed by DSX to properly read the FIPS201 card and insert the proper data into the WinDSX SQL database. CAC Cards may require a different enrollment reader.

Requirements

FIPS 201 Enrollment Reader that is formatted by DSX for WinDSX SQL.

Requires WinDSX SQL version 4.8.75 or higher.

Device Type T5 – No Issue Level

Device Type V6 – Issue Level (recommended)

Connections

Connect Enrollment Reader to a USB Port on a Client PC running WinDSX SQL.

Enrollment Process

Add or Edit a card holder. Advance to the Card screen and click on the Notes field.

Once the cursor is in the Notes field – Present the Card to the Reader by laying the card on top of the reader in the same orientation and letting go.

TEST, New Card

Code #: 0 P.I.N.#

Imprinted Card #: # of Uses Allowed: 9999

Start Date: 06/01/2010 Stop Date: 12/31/9999

Start Time: 12:00:00 AM Stop Time: 12:00:00 AM

Guard Tour: Override Anti-Passback:

Status:

Date Last Used: 01/01/1000 Anti-PassBack Status: N N N N

Last Used At: Loc: 1 COMPUTER ROOM IN Z1 Z2 Z3 Z4

Notes: ^09100000040012255^20141015^

Previous Next Cancel OK

Once the Card is presented the data is briefly shown in the Notes field before it is copied into the Code and Stop Date fields appropriately.

TEST, New Card

Code #: 910000040012255 P.I.N.#

Imprinted Card #: # of Uses Allowed: 9999

Start Date: 06/01/2010 Stop Date: 10/15/2014

Start Time: 12:00:00 AM Stop Time: 12:00:00 AM

Guard Tour: Override Anti-Passback:

Status:

Date Last Used: 01/01/1000 Anti-PassBack Status: N N N N

Last Used At: Loc: 1 COMPUTER ROOM IN Z1 Z2 Z3 Z4

Notes:

Previous Next Cancel OK

Click OK to Save.

(Other Enrollment Readers are available from DSX to properly read different types and formats of Cards.)