

A robust external 35 metre passive infra red intruder detector designed to give reliable event-based triggers that simultaneously or individually control cameras, VCR's, DVR's and all low voltage switching requirements.

# **ADAPTABILITY**

The Elite offers a high level of programmability, there are seven different modes of operation giving various permutations of normally open and normally closed arrangements for the two pairs of volt-free relays, plus a selection of timing and functional options for the relay changeover contacts.

Other programmable parameters include the duration of timed changeover, a pulse count feature and a choice of detection ranges from 10 to 35 metres.

In addition there are two switched negative outputs. The 'A' output gives a single 400ms trigger every time the detector activates and is generally used in conjunction with the GJD lighting controllers to give 24-hour visual and audible alarm indication. The 'S' output is the only photocell-controlled output giving a fixed 60-second trigger on activation.

The flexibility of the four outputs and timers allows the Elite to be used in multiple situations without the need for any further customised equipment.

The integral dual axis tilt sensor allows 180° of pan and 90° tilt. This increases the speed of the outdoor installation and provides incredibly accurate aiming of the detection pattern. The electronics module is acrylic coated for additional component stability. It is encased in a vandal-resistant high impact ABS housing with a UV stabilised translucent front cover ensuring the sensor is impervious to and unaffected by weather conditions.

The Elite's effective design gives a neat appearance with no visible indication of the orientation of the detector head, and totally hides the wiring.

## RELIABILITY


Detecting emitted infrared energy of humans equates to recognising subtle changes of energy in the detectors field of view whilst rejecting changes in other wave lengths that are caused by other factors.

The Elite's custom designed ASIC microprocessor combined with our unique optical system, filters the information received to give the required precision detection performance.

GJD combine this technology with a double silicon shielding of the pyroelectric sensor. The combination of precision electronics, digital white light filter and double shielding resists more than 50,000 lux of unwanted sunlight, therefore eliminating false alarms from visible light sources.

Detection Area  10 to 35 metres (adjustable) up to 750 sq metres  Coverage  90 degree 35 metres x 30 metres max  Adjustment  180 degree pan + 90 degree tilt  Fresnel Lens  36 zone - White Light Filter  Customised Optics  Double silicon shielded dual element eliminates 50,000+ lux of white light  Outputs  Silent solid state magnetically immune  No. I  CCTV output Volt free relay signal contact @ 24VAC/DC @ 50mA with an integral 80R series resistor. Selectable normally open/normally closed. Adjustable timer options: 0.4 to 60 seconds  No. 2  Video output Volt free relay signal contact @ 24VAC/DC @50mA. Selectable normally open/normally closed with an integral 80R series resistor. Adjustable timer options: 2 to 60 seconds  No. 3  Output 'A'  Open collector negative switching - 25mA max. Alarm period 400ms  No. 4  Output 'S'  Open collector negative switching - 25mA max. Alarm period: Detection + 60 seconds Adjustable: Dusk (2 lux) to 24 hour  Power input  9 to 15VDC  Current 10mA (12V nominal)  Pulse Count 1 (2,3 & 4 previous detection ≤ 6 seconds)  Tamper Opens for 2 seconds when cover removed and/or 'A' & 'S' outputs pulse for 60 seconds (progra Temperature Compensation Digital sensitivity adjustment  Operating Temperature  -20 to +55 Centigrade  High Impact ABS	
Adjustment 180 degree pan + 90 degree tilt  Fresnel Lens 36 zone - White Light Filter  Customised Optics Double silicon shielded dual element eliminates 50,000+ lux of white light  Outputs Silent solid state magnetically immune  No. I CCTV output Volt free relay signal contact @ 24VAC/DC @ 50mA with an integral 80R series resistor. Selectab normally open/normally closed. Adjustable timer options: 0.4 to 60 seconds  No. 2 Video output Volt free relay signal contact @ 24VAC/DC @50mA. Selectable normally open/normally closed with an integral 80R series resistor. Adjustable timer options: 2 to 60 seconds  No. 3 Output 'A' Open collector negative switching - 25mA max. Alarm period 400ms  No. 4 Output 'S' Open collector negative switching - 25mA max. Alarm period: Detection + 60 seconds Adjustable: Dusk (2 lux) to 24 hour  Power input 9 to 15VDC  Current 10mA (12V nominal)  Pulse Count 1 (2,3 & 4 previous detection ≤ 6 seconds)  Tamper Opens for 2 seconds when cover removed and/or 'A' & 'S' outputs pulse for 60 seconds (progratementative Compensation Digital sensitivity adjustment  Operating Temperature -20 to +55 Centigrade	
Fresnel Lens  36 zone - White Light Filter  Customised Optics  Double silicon shielded dual element eliminates 50,000+ lux of white light  Outputs  Silent solid state magnetically immune  No. I  CCTV output  Volt free relay signal contact @ 24VAC/DC @ 50mA with an integral 80R series resistor. Selectable normally open/normally closed. Adjustable timer options: 0.4 to 60 seconds  No. 2  Video output  Volt free relay signal contact @ 24VAC/DC @50mA. Selectable normally open/normally closed with an integral 80R series resistor. Adjustable timer options: 2 to 60 seconds  No. 3  Output 'A'  Open collector negative switching - 25mA max. Alarm period 400ms  No. 4  Output 'S'  Open collector negative switching - 25mA max. Alarm period: Detection + 60 seconds Adjustable: Dusk (2 lux) to 24 hour  Power input  9 to 15VDC  Current  10mA (12V nominal)  Pulse Count  1 (2,3 & 4 previous detection ≤ 6 seconds)  Tamper  Opens for 2 seconds when cover removed and/or 'A' & 'S' outputs pulse for 60 seconds (progratementation of the pulse for 50 seconds)  Digital sensitivity adjustment  Operating Temperature  -20 to +55 Centigrade	
Double silicon shielded dual element eliminates 50,000+ lux of white light  Dutputs Silent solid state magnetically immune  No. I CCTV output Volt free relay signal contact @ 24VAC/DC @ 50mA with an integral 80R series resistor. Selectable normally open/normally closed. Adjustable timer options: 0.4 to 60 seconds  No. 2 Video output Volt free relay signal contact @ 24VAC/DC @50mA. Selectable normally open/normally closed with an integral 80R series resistor. Adjustable timer options: 2 to 60 seconds  No. 3 Output 'A' Open collector negative switching - 25mA max. Alarm period 400ms  No. 4 Output 'S' Open collector negative switching - 25mA max. Alarm period: Detection + 60 seconds Adjustable: Dusk (2 lux) to 24 hour  Power input 9 to 15VDC  Current 10mA (12V nominal)  Pulse Count 1 (2,3 & 4 previous detection ≤ 6 seconds)  Tamper Opens for 2 seconds when cover removed and/or 'A' & 'S' outputs pulse for 60 seconds (prografemerature Compensation Digital sensitivity adjustment  Operating Temperature -20 to +55 Centigrade	
Outputs    Silent solid state magnetically immune	
No. I       CCTV oulput       Volt free relay signal contact @ 24VAC/DC @ 50mA with an integral 80R series resistor. Selectable normally open/normally closed. Adjustable timer options: 0.4 to 60 seconds         No. 2       Video oulput       Volt free relay signal contact @ 24VAC/DC @50mA. Selectable normally open/normally closed with an integral 80R series resistor. Adjustable timer options: 2 to 60 seconds         No. 3       Oulput 'A'       Open collector negative switching - 25mA max. Alarm period 400ms         No. 4       Oulput 'S'       Open collector negative switching - 25mA max. Alarm period: Detection + 60 seconds Adjustable: Dusk (2 lux) to 24 hour         Power input       9 to 15VDC         Current       10mA (12V nominal)         Pulse Count       1 (2,3 & 4 previous detection ≤ 6 seconds)         Tamper       Opens for 2 seconds when cover removed and/or 'A' & 'S' outputs pulse for 60 seconds (progratemperature Compensation         Operating Temperature       -20 to +55 Centigrade	
normally open/normally closed. Adjustable timer options: 0.4 to 60 seconds  No. 2 Video output Volt free relay signal contact @ 24VAC/DC @50mA. Selectable normally open/normally closed with an integral 80R series resistor. Adjustable timer options: 2 to 60 seconds  No. 3 Output 'A' Open collector negative switching - 25mA max. Alarm period 400ms  No. 4 Output 'S' Open collector negative switching - 25mA max. Alarm period: Detection + 60 seconds Adjustable: Dusk (2 lux) to 24 hour  Power input 9 to 15VDC  Current 10mA (12V nominal)  Pulse Count 1 (2,3 & 4 previous detection ≤ 6 seconds)  Tamper Opens for 2 seconds when cover removed and/or 'A' & 'S' outputs pulse for 60 seconds (progra Temperature Compensation Digital sensitivity adjustment  Operating Temperature -20 to +55 Centigrade	
with an integral 80R series resistor. Adjustable timer options: 2 to 60 seconds  No. 3	.e
No. 4       Output 'S'       Open collector negative switching - 25mA max. Alarm period: Detection + 60 seconds Adjustable: Dusk (2 lux) to 24 hour         Power input       9 to 15VDC         Current       10mA (12V nominal)         Pulse Count       1 (2,3 & 4 previous detection ≤ 6 seconds)         Tamper       Opens for 2 seconds when cover removed and/or 'A' & 'S' outputs pulse for 60 seconds (progratem perature Compensation)         Digital sensitivity adjustment         Operating Temperature       -20 to +55 Centigrade	
Adjustable: Dusk (2 lux) to 24 hour  Power input  9 to 15VDC  Current  10mA (12V nominal)  Pulse Count  1 (2,3 & 4 previous detection ≤ 6 seconds)  Tamper  Opens for 2 seconds when cover removed and/or 'A' & 'S' outputs pulse for 60 seconds (progratemental progration)  Digital sensitivity adjustment  Operating Temperature  -20 to +55 Centigrade	
Current       10mA (12V nominal)         Pulse Count       1 (2,3 & 4 previous detection ≤ 6 seconds)         Tamper       Opens for 2 seconds when cover removed and/or 'A' & 'S' outputs pulse for 60 seconds (progratemperature Compensation         Digital sensitivity adjustment         Operating Temperature       -20 to +55 Centigrade	
Pulse Count  1 (2,3 & 4 previous detection ≤ 6 seconds)  Tamper  Opens for 2 seconds when cover removed and/or 'A' & 'S' outputs pulse for 60 seconds (progratement temperature Compensation  Digital sensitivity adjustment  Operating Temperature  -20 to +55 Centigrade	
Tamper Opens for 2 seconds when cover removed and/or 'A' & 'S' outputs pulse for 60 seconds (progra Temperature Compensation Digital sensitivity adjustment Operating Temperature -20 to +55 Centigrade	
Temperature Compensation Digital sensitivity adjustment Operating Temperature -20 to +55 Centigrade	
Operating Temperature -20 to +55 Centigrade	mmable)
High Impact ARS	
LIGODILIA LIIINACE VD2	
Protection Rating I P 55	
Dimensions   104 x 100 x 100mm	
Weight 145 grams	
Mounting Height Variable - optimum height 3 metres	
Cable up to 200 metres Utilising all four outputs - 8 core 7/0.2mm Utilising all four outputs - 8 core 16/0.2mm	
Part Number (burgundy) GJD022	
Part Number (white) GJD023	

# GJD ELITE BLOCK DIAGRAM



## **FEATURES**

- Digital ASIC/microprocessor control
   Output test mode with LED indication
   Area reduction mask (if required)
- Non-volatile memory Digital white light filter Wall or pole mounting Conformally coated electronics for increased stability

### **COMPLIANCE**

• High immunity against RFI-BSEN50081-1:1992 • High resistance to EMC-BSEN 50130-4:1996 • GJD's 100% test verification







## FOR FURTHER INFORMATION CONTACT:

GJD Ltd, Kestrel House, Folds Rd, Bolton, BL1 2SD, England. tel: +44 (0) 1204 363998, fax: +44 (0) 1204 363991

### **PART NUMBER: GJD022**

It is our ongoing commitment to continue to develop products of excellence. Due to continued development GJD reserves the right to amend specifications without prior

