FG-1525/1525T

The new FG-1525 Glassbreak Detector uses the latest technology to provide faster response and increased false alarm immunity. The FG-1525 is specifically designed to allow fast, easy installation, while the adjustable sensitivity settings can compensate for the acoustics of any room. Optimum operation can be quickly verified using the FG-701 Glassbreak Simulator.

FEATURES:

• FlexCore™ Signal Processor

The FlexCore Signal Processor is an Application-Specific Integrated Circuit (ASIC), which processes sound data in parallel rather than sequentially for faster, more accurate detection decisions. The combination of proven FlexGuard performance with the speed of FlexCore processing provides unmatched false alarm immunity without compromising detection.

Easy Installation and Setup

IntelliSense's patented technology allows remote activation of Test Mode (w/simulator). The FG-1525 has a centered wire entry hole, 45° terminal blocks, and EOL terminals. A hand-clap feature verifies that the detector is functioning.

Selectable Sensitivity

Two dip switches on the FG-1525 make it easy to set the sensitivity to match the acoustics of the room. Four different sensitivity levels are available, ranging from very low to high. The range can then be verified remotely with the FlexGuard FG-701 Glassbreak Simulator.

• Mount the Detector Anywhere

Mounts on any wall, in the window frame, or on the ceiling, with no minimum range and a maximum range of 25' (7.6 m) to the glass.

Covers All Glass Types

The FG-1525 works on all glass types, including plate, tempered, laminated, wired, film-coated, and sealed insulating glass.

FlexCore Parallel Signal Processing

Sound wave signals are processed by the ASIC in parallel, rather than in sequence. This enables the detector to process 50% more data in less time, ensuring better detection and false alarm immunity.

Multiple Domain Signal Analysis

The FG-1525 performs
Multiple Domain Signal
Analysis in which time,
frequency and amplitude
characteristics are evaluated
for signal qualification. This enables the
detector to accurately discriminate false
alarms from true glassbreak events.

• Installer-Friendly Terminal Blocks

Terminal blocks have 45° angle entry and added positions for EOL resistors.

Enclosed PC Board

The PCB is protected from potential damage during installation.

• Remote LED Enable/Disable

Remotely enable or disable the indicator LEDs using the FG-701 Glassbreak Simulator.

Patented Remote Test Mode Enable/Disable

Test Mode can be enabled or disabled remotely using the FG-701. The unit automatically resets from Test Mode in five minutes.

Power Up Self-Test

The unit performs a series of self-tests upon power up. If any self test fails, the unit will signal trouble by alternately flashing the indicator LEDs.

Mounting Locations

The FG-1525 can be mounted on the ceiling, opposite wall, adjoining wall, or the same wall as the glass.

Glassbreak Detector



FG-1525/1525T

SPECIFICATIONS:

Physical Dimensions:

White high impact ABS plastic housing 3 7/8" H x 2 2/5" W x 7/8" D (98 mm x 62 mm x 21.8 mm)

Weight:

Product Only: 3.2 oz (90g) Pkgd Product: 4.1 oz (116g)

Range:

25' (7.6 m) maximum, omnidirectional. Range is adjustable; no minimum range

Alarm Relay:

FG-1525: Form A, 125mA max, 25VDC max FG-1525T: Form C, 125mA max, 25VDC max

Tamper Switch (FG-1525T only):

Combination cover/wall tamper 25mA max, 24VDC max

Alarm Duration:

Five seconds (unaffected by alarm LED latching)

ESD Immunity:

10kV discharges of either polarity to exposed surfaces

Power Requirements:

6 - 18VDC, 12mA typical at 12VDC; 22mA max (Latched LED) AC ripple: 4V peak-to-peak at nominal 12VDC

RFI Immunity:

30V/m. 10MHz - 1000MHz Operating Temperature: 14° to 122° F (-10° to 50° C)

Storage: -4° to 122° F (-20° to 50° C)

Approvals and Listings:

FCC and IC verified CE C-Tick **UL** Listed **ULC** Listed









CE

ORDERING:

Part No.

Description

FG-1525 FG-1525T Glassbreak Detector Glassbreak Detector with Tamper

Glass Type/Thickness

Type*	Minimum	Maximum
Plate 3a	2.4 mm (3/32")	10 mm (3/8")
Tempered	3 mm (1/8")	10 mm (3/8")
Laminated 1	3 mm (1/8")	14 mm (9/16")
Wired	6 mm (1/4")	6 mm (1/4")
Coated 2,3b	3 mm (1/8")	6.4 mm (1/4")
Sealed	3 mm (1/8")	6 mm (1/4")
Insulating 1,3b	(Maximum overall	
	7/16")	

- * Minimum size for all types is 28 cm (11") square; glass must be framed in the wall or mounted in a barrier at least 0.9 m (36") wide.
- Protected only if both plates of the unit are broken.
- Coated glass with security films, including films for solar protection, up to 12 mil. thick may be used. Film Technologies International, Inc.'s GLASS-GARD® GGLL 1200 has been evaluated with this product by Underwriters Laboratories, Inc. at IntelliSense's request.
- In compliance with Underwriters Laboratories of Canada's Standard for Intrusion Detection Units (CAN/ULC-S306-M89):
 - a. Plate glass 3mm to 10mm can be used.
 - b. ULC recognizes a maximum range for protecting sealed insulated glass and coated glass of 12.5 ft. (3.8 m).

Note: The FG-1525/1525T detects shattering of framed glass by direct impact. It may not consistently detect breakage by blows that only crack the glass, by high velocity projectiles such as bullets, or glass broken without an impact.

Accessories

FG-701 P/N 0-000-701-0

FG-SP1 P/N 0-010-700-01 Spacer Plate depth of 0.6" [15.2 mm] FG-SP3 P/N 0-010-704-01 Spacer Plate (ships with product) depth of 0.3" [7.6 mm]

FlexGuard® Glassbreak Simulator/Tester

Description

Glassbreak Simulator

The sound of breaking glass is digitally simulated by the FG-701. The FG-701 is compatible for testing all IntelliSense glassbreak detectors. IntelliSense highly recommends testing glassbreak detectors before final installation.

© 2002 IntelliSense® • IntelliSense and FlexGuard are registered trademarks of Honeywell, Inc. . All other trademarks are the properties of their respective owners. • All rights reserved.

Glassbreak **Detector**

> 165 Eileen Way, Syosset, NY 11791 Copyright ©2002 Pittway Corporation ADEMCO is an ISO9001 Registered Company

