




Interactive Technologies, Inc.

WIRELESS

Security
Automation
Access Control

4-Button Keychain Touchpad



File: Sensors

ITI Part # 60-606-319.5

Overview

The wireless 4-Button Keychain Touchpad makes ITI security systems easier to use than ever before. This small but powerful touchpad acts like an electronic key. It can arm or disarm the system, activate the police or auxiliary panic alarm, and turn lights on or off from up to 500 feet away. With the Security Pro 4000, the Keychain Touchpad can also turn the Energy Saver Module on or off, make lights flash on and off, and operate a garage door opener.

The Keychain Touchpad fits on a keychain, in a pocket, or in a purse, and is added to the system either as a sensor or as a wireless touchpad in a few simple steps.

The 4-Button Keychain Touchpad is compatible with the following security systems:

- Security Pro 2000 software version 4.0 (60-437-95-8Z-SEC or 60-437-95-17Z-SEC)
- Security Pro 4000 software version 3.0 (60-435-10-95-SEC)

Applications

4-Button Keychain Touchpads are recommended for

- Controlling a Security Pro 2000 or 4000 system from a distance
- Home automation convenience
- Turning individual lights on and off with the same remote control that operates some of your security system functions

Functions

4-Button Keychain Touchpads can perform the following functions:

- Arm the system (with or without delay)
- Disarm the system
- Send a panic alarm
- Control lights individually
- Send an auxiliary panic alarm
- Control the Energy Saver Module (Security Pro 4000 only)

4-Button Keychain Touchpad

Specifications

Battery	12 VDC, 33 mAh alkaline battery
Battery Type	NEDA 1811A
Battery Brand	Duracell MN21
Typical Battery Life	5 to 8 years under recommended operating conditions
Transmitter Frequency	319.5 MHz (crystal-controlled)
Transmitter Frequency Tolerance	± 5 kHz
Transmitter Bandwidth	24 kHz
Modulation Type	Amplitude Shift Key (ASK)
Unique ID Codes	16 million
Peak Field Strength	> 40,000 µV/m @ 3m
Operating Temperature	10°F (-12 °C) to 120°F (49 °C)
Enclosure	ABS Plastic
Weight	0.8 oz (22.68 g)
Dimensions	1.375 in (3.5 cm) wide x 2.25 in (5.7 cm) long x 0.375 in (0.95 cm) thick
Color	Black
FCC Standard	CFR Chapter 47, FCC Part 15

Installation

System Programming The touchpad can be added to the system as a sensor or wireless touchpad. If added as a sensor, the panel identifies the touchpad by its sensor number and reports this number to the central station. Also, the touchpad can be bypassed, which disables all touchpad functions.

If the touchpad is added as a wireless touchpad, the panel identifies it as user number 20* or user number 41[†] and reports this number to the central station. When added as a wireless touchpad, it cannot be bypassed.

Activating Tamper Activate the tamper switch by pressing the top 2 buttons at the same time while the system is in program mode. This action adds the touchpad to the system memory.

*Security Pro 2000

[†] Security Pro 4000

Interactive Technologies, Inc.
2266 Second Street North
North Saint Paul, MN 55109
1-800-777-5484
Fax: 1-612-779-4890

Specifications are subject to change without notice.

Ordering Information
ITI Part # 60-606-319.5

ITI Document # 466-1050 (Rev. A)
(Spec Sheets available in quantities of fifty)

ITI is a registered trademark of Interactive Technologies, Inc.