

# KBD300A

Home | Security | Processing | Accessories

## KBD300A

System Keyboard with Joystick for Pelco Matrix Switchers CM6700/6800 and Esprit,

Art-Nr. 73743



## Main Features

Programming and Control of CM6700/6800 Matrixes  
Joystick Control of PTZ Functions  
Direct Mode Operation of Spectra and Esprit  
Automatically Recognizes Mode of Operation

Programmable Sequences/Patterns  
Preset Position and Pattern Control  
Auto/Random and Frame Scanning  
Auxiliary Operation

## Specifications

### Site control (direct mode operation)

Camera functions: pan, tilt, zoom, focus, iris for fixed or variable speed control of the VPT-41RSP/PT (fixed speed only), VPT-42RSP/PO P/T head series, Spectra dome camera series and the Integrated Positioning system Esprit

### Direct mode

RS-422 Interface. Protocol: Pelco P Baud rate: 4800, Communication parameters: 8 data bits, 1 stop bit, no parity

### Camera control (CM6700 and CM6800)

Keys select cameras and monitors, operate presets, patterns, auxiliaries, and sequences Camera functions: pan, tilt, zoom, focus, iris for fixed or variable speed control of the VPT-41RSP/PO (fixed speed only), VPT-42RSP/PO P/T head series, Spectra dome camera series and the Integrated Positioning system Esprit

### Matrix communication

RS-485 Interface. Protocol: Pelco ASCII Baud rate: 9600, Communication parameters: 8 data bits, 1 stop bit, odd parity

### Interface

RS-422/RS-485, RJ45 (8-pin)

### Display

2x7-segment digital display

# KBD300A

(Continuation Spezifications)

|                    |                   |
|--------------------|-------------------|
| Supply voltage     | 12VAC/DC*)        |
| Power consumption  | 1W                |
| Dimensions (HxWxD) | 57.2x241.3x181 mm |
| Weight             | 1.1 kg            |
| Certificates       | CE                |

## Optional accessories

|       |                |                                                       |
|-------|----------------|-------------------------------------------------------|
| 73419 | KBDKIT-X       | Connection Kit for KBD Keyboards                      |
| 98466 | KBD300USBKIT-X | USB Kit for Installation of KBD300A to DX4500, DX4600 |

# KBD300A

## Product information

\*) For direct connection to the CM6700 and CM6800 matrix switcher control system, Spectra dome camera series and the Integrated Positioning system Esprit no separate power supply is necessary (up-to 7.5m distance). For longer distances the connection kit KBDKIT must be used.



**VIDEOR**