

# HUNTER-PRO 32™

*Comprehensive Hybrid 8 to 32 Zones Alarm System, HUNTER PRO 32 Intrusion Alarm Panel is especially designed to answer your advanced security needs by using the latest technology*

## Features & Benefits:

- \* 8 to 32 zones with wireless add-on, local, and remote bus expanders
- \* Supports a wide range of partition options:
  - Up to 16 partitions each with its own Account ID and Users
  - Up to 8 subsystems each with different keypads, IDs, etc.
- \* Full supervision data of wireless detectors (life signal, low battery, fault)
- \* Comprehensive Zone Tests for flawless installation: Walk Test, Soak Test, etc.
- \* Two options for viewing system status:
  - "PIMA" Style: Status of all 32 zones is displayed simultaneously
  - Detailed: Scrolling events, zones' and system's status
- \* Four Subscriber dialing numbers with optional voice message
- \* Four Monitoring Stations phone numbers
- \* PIMA unique Integrated Digital Communicator (telephone, long-range radio and/or GSM)
- \* Supports split and double reporting to two monitoring stations with different account IDs
- \* LCD keypad with multilingual Menu-Driven screens for easy programming and operation
- \* Many alternatives for easy programming (Keypad, Fast Programmer, Local/Remote download software)
- \* Up to 24 users with various authorization levels
- \* Easy and user friendly operation with single key operation
- \* Various accessories (mic, voice unit etc.)
- \* Memory Log up to 410 events (100 non-volatile)
- \* Automatic Arming at a preset time (passive) and/or after a preset silence time (active)
- \* System remote control via any touchtone telephone

## Specifications:

- \* **Operating Temperature:**
  - Control Panel: -30°C to +50°C
  - LCD Keypad: 0°C to +50°C
- \* **Humidity:** 75% (non-condensing)
- \* **Input Voltage:** 14 Vac / 2 A
- \* **Power Consumption:**
  - Control Panel: 44 mA
  - LCD Keypad: 15 mA
- \* **Power Output:** 750 mA / 13.8 Vdc
- \* **Line Protection:** Single or double EOL resistors
- \* **Outputs:**
  - Relay: NO/NC; 1A (on board + 3 on expansion cards)
  - Trans. Outputs: 100 mA max (3 on board + 8 on OUT-1000)
  - Siren Outputs: 2 outputs with thermal fuses
  - Serial Output: RS-232
- \* **Expanders:**
  - OUT-1000: 8 transistor output expansion card
  - EXP-PRO: 8 local wired zones expansion card
  - I/O-8: 8 remote zones expander card (connected to RC-PRO: 16 channels Wireless add-on receiver)
- \* **Communicators:**
  - Telephone (PSTN): Built-in PSTN interface and communicator
  - Long-Range Radio: Built-in communicator with optional Plug-N-Play full-data Radio Transmitter
  - GSM Modem: Built-in communicator with optional Plug-N-Play full-data GSM Transmitter

All specifications are subject to change without prior notice



