

SENTRY

Standard Binary dip switch coding (4,096 combinations, 12 bit)

1&3 channel transmitters and receivers. (*Unlimited number of transmitters can be used with each receiver*).

Superior French Rolling dip switch coding (1,048,576 combinations, 28 bit)

1 & 3 channel transmitters and receivers. (*Unlimited number of transmitters can be used with each receiver*).

High Security Code Hopping factory coded (over 260 million combinations, 66 bit)

1 & 3 channel transmitters and receivers. (*Up to eight transmitters can be used with each receiver*)

Transmitters

- ◆ 1 & 3 channel.
- ◆ Key fob type.
- ◆ Cased in high quality ABS / PVC.
- ◆ 433.92 MHz.
- ◆ Surface mounted technology .
- ◆ SAW resonator stabilised.
- ◆ Power requires internal 12v battery.
- ◆ Output power +/- 0,25mW.
- ◆ Stability +/- 50 KHz.
- ◆ Size- 65mm x 32mm x 14mm.
- ◆ Range up to 100 mtrs (dependent).

Receivers

- ◆ 1 & 3 channel.
 - ◆ 433.92 MHz.
 - ◆ Surface mounted technology.
 - ◆ SAW resonator stabilised.
 - ◆ Latch/pulse selectable.
 - ◆ Normally opened/normally closed.
 - ◆ 12 to 24v AC/DC
 - ◆ Sensitivity 110dBm + .
 - ◆ Potential free
 - ◆ Change over.
 - ◆ 3 Amp maximum.
-