

# SENTRY

**Standard Binary** dip switch coding (4,096 combinations, 12 bit)

1&3 channel transmitters and receivers. (*Unlimited number of transmitters can be used with each receiver*).

**Superior French Rolling** dip switch coding (1,048,576 combinations, 28 bit)

1 & 3 channel transmitters and receivers. (*Unlimited number of transmitters can be used with each receiver*).

**High Security Code Hopping** factory coded (over 260 million combinations, 66 bit)

1 & 3 channel transmitters and receivers. (*Up to eight transmitters can be used with each receiver*)

## **Transmitters**

- ◆ 1 & 3 channel.
- ◆ Key fob type.
- ◆ Cased in high quality ABS / PVC.
- ◆ 433.92 MHz.
- ◆ Surface mounted technology .
- ◆ SAW resonator stabilised.
- ◆ Power requires internal 12v battery.
- ◆ Output power +/- 0,25mW.
- ◆ Stability +/- 50 KHz.
- ◆ Size- 65mm x 32mm x 14mm.
- ◆ Range up to 100 mtrs (dependent).

## **Receivers**

- ◆ 1 & 3 channel.
  - ◆ 433.92 MHz.
  - ◆ Surface mounted technology.
  - ◆ SAW resonator stabilised.
  - ◆ Latch/pulse selectable.
  - ◆ Normally opened/normally closed.
  - ◆ 12 to 24v AC/DC
  - ◆ Sensitivity 110dBm + .
  - ◆ Potential free
  - ◆ Change over.
  - ◆ 3 Amp maximum.
-