

Freewave

wirefree system

	FW/JA63KRX	FW/JA63KXG
Wirefree Zones	16 (twin 32)	
Operating frequency	433 MHz	
Hardwired zones	4 fully programmable zones (NC, EOL or double EOL resistor)	
Zone attributes	Instant, delayed, panic, fire, tamper, next delayed.	
Partitions	2 + 1 common area	
Keypads	Max 8 remote controls, 4 hardwired keypads	
Outputs	Alarm relay 1A / 60V Programmable outputs PgX & PgY (chime, fire, arm, panic, alarm, door, home, AC power fail) Siren output (12V / 1A)	
Events memory	127 events with time and date stamp	
Power	240VAC built-in double insulated supply	
Back-up battery	12V 1.2Ah supplied	
Communications	2 voice messages Central station (ARC) Remote access	SMS + Audible to 8 phones 2 x Central station via GSM or GRPS Remote access
Messages	2 x 10 seconds or 1 x 20 seconds voice Sent to 4 telephone numbers	SMS consisting of installation name, source name, time and date.
Supported formats	Ademco, Telemax, Franklin, Radionics, SurGard, DTMF2300, Contact ID.	Contact ID
Operating temperature	-10°C to +40°C	
Complies with	EN50131-1 grade 2, ETSI EN 300 220, ETS 300 683, TBR-21	
Dimensions	258 x 214 x 77mm + antenna 160mm	

125 Pasture Road, Moreton, Wirral, Merseyside CH46 4TH

Telephone Reception: + 44 (0) 151 606 9595

Telephone sales: +44 (0) 151 606 1000

Fax sales: + 44 (0) 151 606 1122

