

## VMC Joystick



The VMC Joystick is a stand-alone USB input device for systems running on Microsoft Windows operating systems. Once connected, it is installed automatically using the standard driver that is integrated in the operating system and enables the control of any number of applications. In connection with a Dallmeier PVS 7 and the Dallmeier software PView 7 or SeMSy® it allows for the remote control and display of up to 24 cameras per recorder. The joystick's ergonomic design and compact construction form allows a user-friendly and efficient operation even in the most confined space.

- Suitable for Microsoft Windows XP / 7 systems
- Automatic installation through standard driver
- Control of any application
- Camera control via PVS 7 and PView 7 or SeMSy®
- Control of up to 24 PTZ cameras per DVR
- Supports the control protocols DCCD, Pelco D and Pelco P etc
- User-friendly tri-axial mechanics
- USB interface
- Baud rate from 2,4 up to 57,6 kbps
- DIN EN 50130-4 certified

### Options

#### Item number

**002192 VMC Joystick (with 200 cm USB cable)**  
Joystick module of the VMC-1 control panel as stand-alone device for controlling of PTZ dome cameras at workstations

## VMC Joystick

**Technical Specifications**

Type	Tri-axial
Baud rate	2.4 kbps up to 57.6 kbps
Interface	USB 2.0, Type B
Control protocol	DCCP, Pelco D, Pelco P
Voltage supply	5 V DC (via USB)
Power consumption	Max. 2.5 W
Operating temperature	+5°C to +35°C
Humidity	10 – 70% RH, non-condensing
Dimensions	Approx. 138 x 128 x 224 mm
Weight	Approx. 900 g
Approvals/certifications	CE, DIN EN 50130-4

Technical drawings

