



3 GALLIFORD ROAD INDUSTRIAL ESTATE  
HEYBRIDGE  
MALDON  
ESSEX CM9 4XD

TEL: MALDON (01621) 856850  
FAX: MALDON (01621) 856162  
Email: [yantech@yantech.uk.com](mailto:dantech@yantech.uk.com)  
Website: [www.yantech.uk.com](http://www.yantech.uk.com)

## PRODUCT DATA SHEET FOR DA395

### PRODUCT DESCRIPTION

A power supply with 2 x 1 Amp 12V DC (13.7) output, which will house and charge one VRLA battery up to 7Ah capacity. Typical uses are for powering door access controllers, electric releases and maglocks and CCTV cameras.

### PRODUCT SPECIFICATION

#### General Electrical and Mechanical Specification

- Supply Voltage: \_\_\_\_\_ 240V AC 50Hz
- Current Consumption: \_\_\_\_\_ < 150VA at full load
- Colour: \_\_\_\_\_ White
- Size in mm (W x H x D): \_\_\_\_\_ 210 x 260 x 80
- Weight in Kg: \_\_\_\_\_ 3.63
- Packed Size in mm (W x H x D): \_\_\_\_\_ 218 x 280 x 83
- Packed Weight in Kg: \_\_\_\_\_ 3.8
- Case Material: \_\_\_\_\_ 1.2 mm Powder coated Mild Steel
- Operating Temperature: \_\_\_\_\_ -10 to +40°C
- Storage Temperature: \_\_\_\_\_ -20 to +50°C
- Operating Relative Humidity: \_\_\_\_\_ up to 95% non condensing
- MTBF: \_\_\_\_\_ 50,000 hours
- CE approved: \_\_\_\_\_ Yes

#### Other Relevant Specification

- Output Voltage: \_\_\_\_\_ 12V DC (nominal 13.7V DC)
- Current: \_\_\_\_\_ 2 x 1A
- Mains Fail Indication: \_\_\_\_\_ No
- Low Volts Indication: \_\_\_\_\_ No
- Recommended Battery Size: \_\_\_\_\_ 7Ah
- Fan Cooled: \_\_\_\_\_ No
- Tamper Switch: \_\_\_\_\_ No

Registered Proprietor: Benham (General Engineers) Ltd. No. 1181752  
Registered at 3 Galliford Road Industrial Estate, Heybridge, Maldon, Essex CM9 4XD, England  
Directors: R. A. Scott K. E. Horwood A. D. Matthews N. J. Scott

VAT Reg. No. GB 282 7627 31