

# ENFORCER®

## Miniature Electromagnetic Lock

### Model: E-941SA-300

- Perfect for cabinets, drawers, or small enclosures
- Holding force: 300lb. (136kgs)
- Anodized aluminum housing
- No residual magnetism
- Detachable mounting bracket for easy installation
- MOV surge protection
- Complete mounting hardware included
- 36-inch hookup wire included

E-941SA-300	
Magnet size	6 <sup>3</sup> / <sub>4</sub> x 1 <sup>5</sup> / <sub>16</sub> x 1 <sup>1</sup> / <sub>4</sub> " 170 x 23 x 32mm
Armature size	6 x 3 <sup>3</sup> / <sub>8</sub> x 1 <sup>1</sup> / <sub>4</sub> " 152 x 10 x 32mm
Holding force	300lb (136kg)
Current Drain	315mA/12VDC
Voltage Tolerance	±10%
Temperature	(-10 <sup>0</sup> to 55 <sup>0</sup> )C (14 <sup>0</sup> to 131 <sup>0</sup> )F
Unit Weight (Approx.)	2.84lbs. (1.29 kg)



**NEW!**

CE

## Two Additional Models to Choose From:

**E-941SA-1200 Holding force: 1200lb. (545 kg.)**

**E-941SA-600 Holding force: 600lb. (272 kg.)**

- Anodized aluminum housing
- Dual voltage: 12 or 24 VDC (selectable)
- No residual magnetism
- Detachable faceplate
- Adjustable mounting bracket
- MOV surge protection
- Complete mounting hardware included
- "L" brackets, "Z" brackets, and spacers available separately



E-941SA-1200  
10<sup>1</sup>/<sub>2</sub> x 1<sup>5</sup>/<sub>8</sub> x 2<sup>5</sup>/<sub>8</sub>"  
268 x 42 x 67mm

E-941SA-600  
9<sup>7</sup>/<sub>8</sub> x 1<sup>1</sup>/<sub>16</sub> x 1<sup>5</sup>/<sub>8</sub>"  
250 x 27 x 42mm

CE

The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

For more information, contact

**SUPERIOR ELECTRONICS CORPORATION**

P.O. BOX 57-81, TAIPEI 106, TAIWAN, R.O.C.

Copyright © 2000 SECO-LARM®. All right reserved.

Tel: 886-2-2378-6161 / Fax: 886-2-2378-6163

E-mail: [info@superior-elec.com](mailto:info@superior-elec.com)

Url: <http://www.enforcer.com.tw> or [www.superior-elec.com](http://www.superior-elec.com)